

# 943 NETWORK COMPONENTS

## ACTIVATOR 3M

Code : **9430042**

Model : **CER-011**

### Description

Activation device with 1,5m of coverage radio for waking up wandering control tag bracelets that are placed near the area to be controlled (door, corridor, etc.) It sends an electromagnetic signal (125KHz) to tag bracelets (CER-030) with its identifier. Once the bracelet receives this signal, it sends a message in 13,56 MHz to the area controller central (CER-025) indicating activator and tag identifiers. As long as the bracelet (CER-030) remains within the range of the activator, it will continuously activate the bracelet until the wanderer leaves the area. The CER-011 activator must always be placed near the area to be controlled (door, corridor, etc.) CER-011 has a range of 3 m.

9430042

CER-011

### Especificaciones

Frecuencia	125 kHz
Alimentación	12V/24V
Consumo	110 mA
Potencia radiada	<25mV
Temperatura de funcionamiento	20 De -20 a 55°C
Estanqueidad	IP66
Dimensiones	205 x 183 x 14 mm
Área de activación	3 m