

903 MAST AMPLIFIERS

KIT AMP AM-396 & POWER SUPPLY 24 VDC



Code : **9030208**

Model : **BO-396**

Description

Kits consisting of an AM-396 mast amplifier and an AL-100 power supply unit. Both products are included in a single pack.

Characteristics

The characteristics are identical to those of the products which are supplied independently.

CÓDIGO-CODE-CODE		9030193	9030195			9030207			
MODELO-MODEL-MODELE		AM-195	AM-296			AM-396			
Número de entradas Number of inputs Nombre d'entrées		1	2			3			
Rango de frecuencia Frequency range Gamme de fréquences	Band	UHF	FM	DAB	UHF	FM	DAB	UHF	UHF2
	MHz	470-694	88-108	160-260	470-694	88-108	160-260	470-694	470-694
Ganancia Gain Gain	dB	32	20		32	20		32	
Regulación de ganancia Adjustable gain range Plage de réglage du gain	dB	16	20		16	20		16	
Nivel de salida Output level Niveau de sortie	dB μ V	108		DIN 45004B					
		105		(IMD ₃ -66 dB)					
		93		(IMD ₂ -60 dB)					
Figura de ruido Noise figure Facteur de bruit	dB	3,5 \pm 1	5,0 \pm 1	3,5 \pm 1	5,0 \pm 1	6,0 \pm 1			
Rechazo entre entradas Rejection between inputs Rejection entre entrées	dB	≥ 30							
Alimentación Power supply Alimentation	V \dots	24							
	mA	30							
Paso de corriente DC path Passage d'alimentation	V \dots	24	-	24	-	24			
	mA	50	-	50	-	50			
Temperatura de funcionamiento Operating temperature Température de fonctionnement	°C	-20..+65							
Índice de protección Protection index Indice de protection		IP 33							