

# 941 CAPTEURS

---

## INTERRUPTEUR MURAL D'ANNULATION D'APPEL

Code : **9410360**

Modèle : **LLC-833**

Bloc mural avec 1 bouton (annulation).



CÓDIGO-CODE-CODE	9410352, 9410351, 9410353, 9410360, 9410354, 9410355, 9410356, 9410357, 9410358, 9410359		9410370, 9410371, 9410372, 9410373, 9410374, 9410375, 9410376, 9410377, 9410378,	
MODELO-MODEL-MODÈLE	LLC-83X, LLC-84X		LLC-93X, LLC-94X	
Color de Botón Push button color Boutons couleur	<b>Verde, Green, Vert:</b> LLC-X30, LLC-X31, LLC-X32, LLC-X42, LLC-X43 <b>Azul, Blue, Bleu:</b> LLC-X32, LLC-X41, LLC-X43, LLC-X47 <b>Rojo, Red, Rouge:</b> LLC-X32, LLC-833, LLC-X40, LLC-X42, LLC-X48 <b>Amarillo, Yellow, Jaune:</b> LLC-X31, LLC-X32			
Alimentación Power supply Alimentation	24V			
Consumo (stand by) Energy consumption (stand by) Consommation (stand by)	10 mA			
Consumo (max.) Energy consumption (max.) Consommation (max.)	40 mA			
Dimesiones Size Dimensions	80x80x10mm			
Peso Weight Poids	0,08Kg			
Material Material Matériel	ABS/Polycarbonate			
Color Color Couleur	Blanco, White, Blanc (RAL 9001)			
Temperatura operacional Operating temperature Température de fonctionnement	5°C - 55°C			
Indice de protección Protection Indice de Protection	IP 42			
Instalación Mounting Installation	Empotrado, Embedded, Encastré (ACC-100 / ACC-101) En superficie, On surface, En saillie (ACC-110)			
Normativa (seguridad) Normative (security) Norme (sécurité)	EN 60950-1:2006			
Normativa (emisiones electromagneticas) Normative (electromagnetic emissions) Norme (champs magnétique)	EN 61000-3-3			
Conector de red Net Connector Connexion	Bornas, Contact: 8XX	RJ45: LLC-9XX		