

941 SENSORS AND ACTUATORS

REMOTE RECEIVER WITH 8 RELAY OUTPUTS

Code : **9410074**

Model : **SNI-108**

Description

Wireless receiver with 8 output contact that is connected to room control panel CHC. It receives activation signals from wireless sensors and emergency push-buttons and notifies them to the room control panel to be communicated to ALCAD NURSE CALL system. Up to 8 devices can be differentiated.

SPECIFICATIONS

Current	6 mA resting / 40 mA máx. (at 12VCC)
Voltage	11-15VCC / 11-14VCA
Frequency	868 MHz
Dimensions	110x63x25 mm
Operating temperature	0°C a 49°C
Contact	Normally Open (NO) or Normally Closed (NC)
Relay	1A/48V CA/CC - resistive load
Encoding	Visonic Power Code
Number of outputs	8
Reach	10 m (in open air)
Compatible equipment	SNI-110, SNI-111, SNI-120, SNI-130