

941

SENSORS AND ACTUATORS

NURSE CALL BUTTON WITH LIGHT (DIN8)

Code : **9410314**

Model : **LLC-711**

Description

Handset enables patients to place calls and control the lights. It has a male DIN-8 connector for the LLC-8xx and LLC-9xx wall peripherals. Also, it has a red nurse call button with a red LED and a yellow LED that indicates the state of the connection. This hand-set accessory enables patients to place calls, while the red LED reflects the status of the call. On top of that, up to 2 lights can be controlled with an additional 2 buttons. Bus peripheral with DIN8connector. Easy cleaning and connection.



Code	9410313	9410314	9415049
Model	LLC-710	LLC-711	LLC-712
BOTONES BUTTONS BOUTONS	LLC-710/711/712: Llamada de enfermera/ Nurse call/ Bouton d'appel LLC-711/712: Control de luces / lights control / commande de 2 éclairages* LLC-712: Control de persiana / Blind control / commande des volets roulants*		
LUCES LIGHTS LUMIÈRES	3		
ALIMENTACION POWER SUPPLY ALIMENTATION	24Vdc		
CONSUMO CONSUMPTION CONSOMMATION	2 – 6mA		
TENSION CONTROL DE LUCES LIGHT CONTROL POWER SUPPLY CONSOMMATION	24Vdc		
LONGITUD DEL CABLE CABLE LENTH LONGUEUR DU CORDON	2 m		
TEMPERATURA OPERACIONAL OPERATING TEMPERATURE TEMPERATURE DE FONCTIONNEMENT	-10°C to 55°C		
INDICE DE PROTECCION PROTECTION INDEX INDICE DE PROTECTION	IP40		
DIM.	120 x 60 x 25mm		
PESO WEIGHT POIDS	20gr		
CONECTOR CONNECTOR CONNECTEUR	DIN8 (Macho/Male/Mâle)		

*Modèle livré avec le module de gestion des relais de commandes éclairage et VR.