

941 SENSORS AND ACTUATORS

BLUE CODE AND PRESENCE WALL BUTTONS

Code : **9410357**

Model : **LLC-843**

Push button base, touch version, with antibacterial coating for universal box mounting of the ALCAD brand. It consists of:

- * 1 blue code button with led
- * 1 presence green button with led



CÓDIGO-CODE-CODE			9410352, 9410351, 9410353, 9410360, 9410354, 9410355, 9410356, 9410357, 9410358, 9410359	9410370, 9410371, 9410372, 9410373, 9410374, 9410375, 9410376, 9410377, 9410378,
MODELO-MODEL-MODÈLE			LLC-83X, LLC-84X	LLC-93X, LLC-94X
Color de Botón Push button color Boutons couleur			Verde, Green, Vert: LLC-X30, LLC-X31, LLC-X32, LLC-X42, LLC-X43 Azul, Blue, Bleu: LLC-X32, LLC-X41, LLC-X43, LLC-X47 Rojo, Red, Rouge: LLC-X32, LLC-833, LLC-X40, LLC-X42, LLC-X48 Amarillo, Yellow, Jaune: LLC-X31, LLC-X32	
Alimentación Power supply Alimentation			24V	
Consumo (stand by) Energy consumption (stand by) Consommation (stand by)			10 mA	
Consumo (max.) Energy consumption (max.) Consommation (max.)			40 mA	
Dimesiones Size Dimensions			80x80x10mm	
Peso Weight Poids			0,08Kg	
Material Material Matériel			ABS/Polycarbonate	
Color Color Couleur			Blanco, White, Blanc (RAL 9001)	
Temperatura operacional Operating temperature Température de fonctionnement			5°C - 55°C	
Indice de protección Protection Indice de Protection			IP 42	
Instalación Mounting Installation			Empotrado, Embedded, Encastré (ACC-100 / ACC-101) En superficie, On surface, En saillie (ACC-110)	
Normativa (seguridad) Normative (security) Norme (sécurité)			EN 60950-1:2006	
Normativa (emisiones electromagneticas) Normative (electromagnetic emissions) Norme (champs magnétique)			EN 61000-3-3	
Conector de red Net Connector Connexion			Bornas, Contact: 8XX	RJ45: LLC-9XX