

912 TV-SAT AND MODULATOR EQUIPMENT

QUAD LNB, UNIVERSAL

Code : **9120264**

Model : **UE-301**

Universal quad LNB for offset parabolic antennas, for individual installations.

High stability in frequency and high gain. The very low noise level provides quality reception in areas of weak signal.



| CÓDIGO-CODE-CODE | | 9120262 | 9120263 | 9120264 | 9120265 |
|---|--------------|--|--------------------------|------------------------|--------------------------|
| MODELO-MODEL-MODÈLE | | UE-005 | UE-203 | UE-301 | UE-404 |
| Tipo de LNB LNB type Type de LNB | | single | twin | quad | quattro |
| Salidas Outputs Sorties | | 1 | 2 | 4 | 4 |
| Tipo de conector Conector type Type de connecteur | | F | | | |
| Frecuencia de entrada Input frequency Fréquence d'entrée | GHz | banda baja / low band / bande basse 10,70 – 11,70 banda alta / high band / bande haute 11,70 – 12,75 | | | |
| Frecuencia OL LO frequency Fréquence OL | GHz | banda baja / low band / bande basse 9,75 banda alta / high band / bande haute 10,60 | | | |
| Frecuencia de salida Output frequency Fréquence de sortie | MHz | 950 – 2150 | | | |
| Ganancia Gain Gain | dB \pm TOL | 60 \pm 5 | 60 \pm 6 | 55 \pm 8 | 55 \pm 8 |
| Figura de ruido Noise figure Facteur de bruit | dB | > 0,2 (0,6 typ) | | | |
| Alimentación / Conmutación Power supply / Switching Alimentation / Commutation | V- | 13 – 18 / 0 – 22 KHz | | | |
| Polaridades Polarities Polarités | | vertical alta, vertical baja, horizontal alta, horizontal baja high vertical, low vertical, high horizontal, low horizontal verticale haute, verticale basse, horizontale haute, horizontale basse | | | |
| Consumo Consumption Consommation | mA | 115 (max) | 130 (max single port) | 275 (max all ports) | 120 (max single port) |
| Temperatura de funcionamiento Operating temperature Température de fonctionnement | °C | -40...+60 | | | |