

941 SENSORS AND ACTUATORS

NURSE CALL & PRESENCE BUTTON

Code : **9410375**

Model : **LLC-942**



Room touch version peripheral with two buttons: a nurse call button with a red LED and a nurse presence button with a green LED. This peripheral allows patients to call the nurse with the red button. Once initiated the call, the red LED helps to locate the origin of the call easily. The green button is used to either indicate that the nurse is present or to cancel the call. Wall or surface mount.

RJ45 connection.

| CÓDIGO-CODE-CODE | 9410352, 9410351, 9410353, 9410360, 9410354, 9410355, 9410356, 9410357, 9410358, 9410359 | | 9410370, 9410371, 9410372, 9410373, 9410374, 9410375, 9410376, 9410377, 9410378, | |
|---|---|---------------|--|--|
| MODELO-MODEL-MODÈLE | LLC-83X, LLC-84X | | LLC-93X, LLC-94X | |
| Color de Botón Push button color Boutons couleur | Verde, Green, Vert: LLC-X30, LLC-X31, LLC-X32, LLC-X42, LLC-X43 Azul, Blue, Bleu: LLC-X32, LLC-X41, LLC-X43, LLC-X47 Rojo, Red, Rouge: LLC-X32, LLC-833, LLC-X40, LLC-X42, LLC-X48 Amarillo, Yellow, Jaune: LLC-X31, LLC-X32 | | | |
| Alimentación Power supply Alimentation | 24V | | | |
| Consumo (stand by) Energy consumption (stand by) Consommation (stand by) | 10 mA | | | |
| Consumo (max.) Energy consumption (max.) Consommation (max.) | 40 mA | | | |
| Dimesiones Size Dimensions | 80x80x10mm | | | |
| Peso Weight Poids | 0,08Kg | | | |
| Material Material Matériel | ABS/Polycarbonate | | | |
| Color Color Couleur | Blanco, White, Blanc (RAL 9001) | | | |
| Temperatura operacional Operating temperature Température de fonctionnement | 5°C - 55°C | | | |
| Indice de protección Protection Indice de Protection | IP 42 | | | |
| Instalación Mounting Installation | Empotrado, Embedded, Encastré (ACC-100 / ACC-101) En superficie, On surface, En saillie (ACC-110) | | | |
| Normativa (seguridad) Normative (security) Norme (sécurité) | EN 60950-1:2006 | | | |
| Normativa (emisiones electromagneticas) Normative (electromagnetic emissions) Norme (champs magnétique) | EN 61000-3-3 | | | |
| Conector de red Net Connector Connexion | Bornas, Contact: 8XX | RJ45: LLC-9XX | | |