

# 903 MAST AMPLIFIERS

## AMP UHF-UHF-DAB/FM 32 DB LTE MAST 24 VDC



Code : **9030171**

Model : **AM-366**

### Description

Broadband amplifiers for masts, compatible with LTE800 mobile (UHF amplification in the 470-790 Mhz band). They have three inputs to amplify and combine the signals from the antennas. They are fed through the coaxial cable from a power supply unit installed inside the building. They incorporate a switchable DC path, allowing power to be supplied to a preamplifier.

### Applications

Individual digital and analogue terrestrial TV installations which are affected by the transmission of LTE800 mobile phone signals and which require high gain. They amplify and mix the signals from several antennas. The signal obtained can be distributed to a large number of TV outlets by means of a single coaxial cable.

### Characteristics

Shielded zamak chassis, covered by a weather-resistant plastic casing. Easy to open and close, the chassis can be tilted to facilitate manipulation. It can be installed either on a mast, by means of a polyamide clamp, or on a wall. Resistant to sun and water (IP53). Greater insulation between inputs and outputs. F-type connectors for screwing or crimping.

### Accessories

9030086 AL-100 +24 power supply unit. 9120039 CM-004 Male F connector for Ø6.6 mm coaxial. 9080023 MC-302 Male F connector for RG-6 coaxial, Ø7.0 mm. 9080030 MC-304 Male compression F connector for RG-6 coaxial Ø7.0 mm.