

# 941 SENSORES Y ACTUADORES

## RECEPTOR INALAMBRICO CON 1 SALIDA RELE



Código : **9410335**

Modelo : **SNI-301**

### Descripción

Receptor inalámbrico con 1 salida a relé que se conecta a la central de habitación CHC. Recibe la señal de activación de los sensores o pulsadores inalámbricos asociados y la notifica a la central de habitación a la que se conecta emulando la pulsación de un botón para la comunicación de la activación de periféricos inalámbricos al sistema ALCAD NURSE CALL. Control de un único dispositivo inalámbrico.

CODE	9410335
MODEL	SNI-301
Coding	Up to 32 transmitters can be programmed
Frequency	868,30 MHz
Channels	1
Power supply	12-24 V AC/DC
Power consumption	0.35 W standby at 12 V AC, 1.00 W standby at 24 V AC, 0.23 W standby at 12 V DC, 0.60 W standby at 24 V DC, 0.55 W relay switched at 12 V AC (without load), 1.50 W relay switched at 24 V AC (without load), 0.35 W relay switched at 12 V DC (without load), 1.00 W relay switched at 24 V DC (without load)
Operating modes	ON/OFF (2-button operation) ON/OFF (1-button operation) DEADMAN (maximum 36 seconds)
Outputs	1 potential-free relay contact (changeover)
Maximum contact load	1
Operating temperature	-20 °C to +60 °C
Dimensions	46 x 46 x 25 mm

